



Adjusting Time for Daylight Savings

Dejavoo Z Series

From idle screen – Credit Sale Amount

*If device is loaded with Aura Software Press F1 then scroll to Core Menu and Press Enter

*If device is not loaded with Aura Press Green Enter

Scroll down (Using Arrow Key) to Utility – Press Enter

Manager Password – 1234 Press Enter

Settings Highlighted – Press Enter

Date and Time Highlighted - Press Enter

Current Date DD/MM/YYYY – Press Enter

Local Time input HH:MM:SS – Military Time

Press Red Cancel Button to go back to normal Sales screen

Dejavoo QD Series

Press the "Circle" button

Go to Settings

Tap the 3 bars in the top right

Tap Date & Time

Tap Set time

Tap Set date

Press the "Circle" button and go back to the main screen

Tap the AURA app

Dejavoo P Series

Scroll down from the top of the screen

Tap on the gear in the top right

Tap Date & Time

Tap Set time

Tap Set date

Press the back button until you return to the sales screen

ChargeAnywhere Q Series

Settings

About pos

Pos configuration

Administrator login

99999999 (number 9 eight times in a row)

Back until main settings section

3 lines at top right

Date & time

Disable automatic time zone

Set to appropriate time zone

VeriFone VX520

From idle Screen – Sale / Card Verify / Settlement

Press Green Enter Button
Setup Highlighted Press Enter
Password – 998877 Press Enter
Scroll down (More Key) 4 x's to get to option for Date and Time
Press F4 to change Date and Time
Input Date MM/DD/YYYY 11/01/2020 Press Enter
Input Time HH:MM:SS 10:30:00 Press Enter
Press Red Cancel Button to go back to normal Sales screen

Ingenico Tetra Series

From the normal idle screen

Menu (target/circle) button
UP arrow
Control panel
Up arrow
Terminal settings
General Settings
DOWN arrow
Date and Time
Set Time
Green Enter
Red X back to home screen

Valor Terminals

No adjustment required as the network platform they are connected to automatically adjusts proper time

PAX Terminals

No adjustment required as the network platform they are connected to automatically adjusts proper time